

Management Conf.

```
bridge add 1-1-4-0-eth t1s vlan 100 tagged
interface add 1-1-6-0/ipobridge vlan 100 10.185.78.58/23
route add default 10.185.78.1 1
update system sysname = Chedi-GPON 0
setprompt user Chedi-GPON>
setdatetime 12 16 2024 14 26 00
```

Uplink Bridges Conf.

```
bridge add 1-1-4-0/eth uplink vlan 202 tagged igmpproxy
bridge add 1-1-4-0/eth uplink vlan 242 tagged igmpproxy
bridge add 1-1-4-0/eth uplink vlan 182 tagged
bridge add 1-1-4-0/eth uplink vlan 2760 tagged
bridge add 1-1-4-0/eth uplink vlan 416 tagged
bridge add 1-a-1-0/eth uplink vlan 0 slan 395 stagged
bridge add 1-1-3-0/eth t1s vlan 182 tagged
new cpe-voip-server 172
new cpe-ip-server 172
```

Speed limit rule

```
Rule : rule add ratelimitdiscard 5/1 rate 3000 peak 4000
```

```
Bridge : bridge add 1-1-1-9/gpononu downlink vlan 85 tagged rg-brouted eth 3 epktrule 5 ipktrule 5
```

Search for ONU

```
onu find fsan 3aa5fd4
```

Downlink Bridges Conf.

```
bridge add 1-1-6-901/gponport gtp 10 downlink-video vlan 238 tagged video 0/5 rg-bridged eth 1
bridge add 1-1-6-2/gpononu downlink vlan 3990 slan 397 tagged maxunicast 100 eth [2-4] wlan 1 rg-brouted
bridge add 1-1-6-2/gpononu downlink vlan 3990 slan 397 tagged maxunicast 100 eth [2-4] rg-brouted
```

cpe wlan add 1/6/1/1 admin-state down

cpe wlan add 1/6/1/1 ssid somy encrypt-key 27051956 wlan-com-profile 2

bridge add 1-1-8-701/gponport gtp 2 downlink vlan 40 tagged sip rg-bridged

cpe voip ip add 1/8/1 ip-com 40

cpe voip add 1/8/1/1 dial-number 76210 username 76210 password 176210 voip-server-profile 40

Gtp Conf.

new gpon-traffic-profile dba-enabled = true dba-fixed-us-ubr-bw = 128 dba-assured-us-bw = 10112 dba-max-us-bw = 10240 traffic-class = ubr 10

new gpon-traffic-profile dba-enabled = true dba-fixed-us-ubr-bw = 128 dba-assured-us-bw = 101120 dba-max-us-bw = 102400 traffic-class = ubr 100

new gpon-traffic-profile dba-enabled = true dba-fixed-us-ubr-bw = 128 dba-assured-us-bw = 20224 dba-max-us-bw = 20480 traffic-class = ubr 20

new gpon-traffic-profile dba-enabled = true dba-fixed-us-ubr-bw = 128 dba-assured-us-bw = 256 dba-max-us-bw = 2048 traffic-class = ubr 2

update cpe-cfg-global-settings 0

onu set 1/2/1 meprof zhone-2424 vendorid ZNTS serno fsan 03AA6362

onu profile show internal-me

cpe rg lan ip-com show 100001

cpe rg lan ip-com modify 100001 primary-dns 41.128.225.225 secondary-dns 41.128.225.226 mtu 1492

cpe rg lan dhcp-srvr show 100001

Add new slot

card add 4